

2350 Induced Voltage Filter



The 2350 Induced Voltage Filter (IVF) is a central office installed unit designed to provide maximum protection against 180/300 Hz induced power line currents and electrical noise. The unit is an environmentally sealed 180/300 Hz series pass filter and is connected between the protected shield armor and ground.

The IVF is a tuned series pass network which provides a low impedance path to ground for 180/300 Hz induced currents. The 180/300 Hz influence is induced into communication cables which are placed in close proximity to power lines. The IVF shunts the 180/300 Hz currents to ground while allowing low voltage monitoring, locate tones, and fault locate signals to pass.

Features

- Provides low impedance ground path for 180/300 Hz induced voltages
- Continuous operation
- Designed for indoor use
- Rated at .5 amp continuous current
- Wall mount bracket included
- Standard 16 gauge copper leads

Specifications

ITEM	QUANTITY/SPECIFICATION	NOTES
Induced Voltage Filtering		
Voltage Reduction Ration (typical) (Z _{source} = 200Ω, IF = 1 amp)	7:1	VI / Vf
Maximum Voltage (Continuous)	20 V	AC RMS
(5 min)	250 V	AC RMS
Clamping Voltage (typical)	15V	AC RMS
Impedance (nominal)	30 Ω @ 60 Hz (I = 1 amp) 1200 Ω @ 30 Hz 7000 Ω @ 512 Hz	
Physical		
Dimensions	4.2" x 2.8" x 2.4" (10.2 cm x 7 cm x 6 cm)	
Weight	3.5 lbs (1.6 kg)	
Model Number(s)		
Central Office/Remote Office	Indoor – Cable Vault	
Model Number(s)	2350 IVF	#16 Gauge Leads

PROVIDES LOW IMPEDANCE GROUND PATH FOR 60 HZ INDUCED VOLTAGES

CONTINUOUS OPERATION

DESIGNED FOR INDOOR USE

RATED AT .5 AMP CONTINUOUS CURRENT

WALL MOUNT BRACKET INCLUDED

STANDARD 16 GAUGE COPPER LEADS

For more information on any of our products or services, please visit us on the web at:
www.norscan.com

10 TERRACON PLACE
WINNIPEG, MB R2J4G7
P: 204.233.9138
F: 204.233.9188
SALES@NORSCAN.COM
WWW.NORSCAN.COM

SPECIFICATIONS SUBJECT TO CHANGE WITHOUT NOTICE

norscan
Instruments Ltd.